



PRINCIPLES OF COMMUNICATIONS

Systems, Modulation, and Noise

Fourth Edition

R. E. Z I E M E R

University of Colorado at Colorado Springs

W. H. T R A N T E R

University of Missouri-Rolla



JOHN WILEY & SONS, INC.

New York • Chichester • Brisbane • Toronto • Singapore



Cover designer: DesignHeads, Boston

Cover image: Andrea Way, Tidepool, 1988.

Ink and pencil on paper, 36 x 51½"

Private collection

Courtesy Brody's Gallery, Washington DC

Copyright © 1995 by John Wiley & Sons, Inc.

Previously published by Houghton Mifflin Company.

Reproduction or translation of any part of this work beyond that permitted by Sections 107 and 108 of the 1976 United States Copyright Act without the permission of the copyright owner is unlawful. Request for permission or further information should be addressed to the Permission Department, John Wiley & Sons, Inc.

ISBN: 0 471 12496 6

Printed in the United States of America

10 9 8 7 6 5 4 3

6	NOISE IN MODULATION SYSTEMS	394
6.1	<i>Signal-to-Noise Ratios</i>	395
6.2	<i>Noise and Phase Errors in Coherent Systems</i>	408
6.3	<i>Noise in Angle Modulation Systems</i>	414
6.4	<i>Thresholds and Threshold Extension in FM</i>	424
6.5	<i>Noise in Pulse Modulation</i>	432
	<i>Summary</i>	441
	<i>Further Reading</i>	443
	<i>Problems</i>	443
	<i>Computer Exercises</i>	451
7	BINARY DATA TRANSMISSION	453
7.1	<i>Baseband Data Transmission in White Gaussian Noise</i>	455
7.2	<i>Binary Synchronous Data Transmission with Arbitrary Signal Shapes</i>	462
7.3	<i>Error Probabilities for Coherent Binary Signaling Schemes</i>	475
7.4	<i>Modulation Schemes Not Requiring Coherent References</i>	482
7.5	<i>Digital Signaling Through Bandlimited Channels</i>	491
7.6	<i>Multipath Interference</i>	497
7.7	<i>Flat Fading Channels</i>	504
	<i>Summary</i>	511
	<i>Further Reading</i>	515
	<i>Problems</i>	515
	<i>Computer Exercises</i>	526
8	ADVANCED DATA COMMUNICATIONS TOPICS	529
8.1	<i>M-ary Data Communications Systems</i>	529
8.2	<i>Bandwidth Efficiencies of Digital Modulation Formats</i>	556
8.3	<i>Synchronization</i>	562
8.4	<i>Spread-Spectrum Communication Systems</i>	570
8.5	<i>Satellite Communications</i>	580
	<i>Summary</i>	594
	<i>Further Reading</i>	596
	<i>Problems</i>	596
	<i>Computer Exercises</i>	601

Quadrature-Amplitude-Shift Keying (QASK)

Another signaling scheme that allows multiple signals to be transmitted using quadrature carriers is *quadrature-amplitude-shift keying* (QASK), which is also referred to as *quadrature-amplitude modulation* (QAM). For example, *M*-QASK utilizes a signal structure similar to that of (8.32) but with the data sequences d_1 and d_2 each taking on \sqrt{M} different possible levels. Thus, for example, we represent the transmitted signal in an arbitrary signaling interval for 16-QASK as

$$s_i(t) = \sqrt{\frac{2E_s}{T_s}} (A_i \cos \omega_c t + B_i \sin \omega_c t), \quad 0 \leq t \leq T_s \quad (8.43)$$

where A_i and B_i take on the possible values $\pm a$ and $\pm 3a$ with equal probability. A signal-space representation for 16-QASK is shown in Figure 8.13(a), and the receiver structure is shown in Figure 8.13(b). The probability of symbol error for 16-QASK can be shown to be

$$P_E = 1 - \left[\frac{1}{4}P(C|I) + \frac{1}{2}P(C|II) + \frac{1}{4}P(C|III) \right] \quad (8.44)$$

where the probabilities $P(C|I)$, $P(C|II)$, and $P(C|III)$ are given by

$$P(C|I) = \left[1 - 2Q\left(\sqrt{\frac{2a^2}{N_0}}\right) \right]^2 \quad (8.45a)$$

$$P(C|II) = \left[1 - 2Q\left(\sqrt{\frac{2a^2}{N_0}}\right) \right] \left[1 - Q\left(\sqrt{\frac{2a^2}{N_0}}\right) \right] \quad (8.45b)$$

$$P(C|III) = \left[1 - Q\left(\sqrt{\frac{2a^2}{N_0}}\right) \right]^2 \quad (8.45c)$$

In the preceding equations $a^2 = E_s/10$, where E_s is the average energy per symbol. The notation I, II, or III denotes that the particular probability refers to the probability of correct reception for the three types of decision regions shown in Figure 8.13(a). This error probability will be compared with that for *M*-ary PSK later. The error probability for 64-QASK or 256-QASK also can be obtained in a straightforward, but tedious, manner.

FIGURE 8.13 Signal space and detector structure for 16-QASK. (a) Signal constellation and decision regions for 16-QASK. (b) Detector structure for 16-QASK. (Binary representations for signal points are Gray encoded.)

