Newnes Dictionary of Electronics Fourth Edition

S. W. Amos, CEng, BSc, MIEE
R. S. Amos, BD, BSc, MISTC
Appendix by
G. W. A. Dummer, MBE, CEng, FIEE



Newnes

OXFORD AMSTERDAM BOSTON LONDON NEW YORK PARIS SAN DIEGO SAN FRANCISCO SINGAPORE SYDNEY TOKYO

Find authenticated court documents without watermarks at docketalarm.com.

Newnes

An imprint of Elsevier Science Linacre House, Jordan Hill, Oxford OX2 8DP 225 Wildwood Avenue, Woburn, MA 01801-2041

First published 1981 Reprinted 1982, 1986 Second edition 1987 Third edition 1996 Reprinted 1997, 1998 Fourth edition 1999 Reprinted 2000 Paperback edition 2002

Copyright © 1999 Elsevier Science Ltd. except Appendix (pp. 359-389) Copyright © 1999 G. W. A. Dummer. All rights reserved

No part of this publication may be reproduced in any material form (including photocopying or storing in any medium by electronic means and whether or not transiently or incidentall to some other use of this publication) without the written permission of the copyright holder except in accordance with the provisions of the Copyright, Designs and Patents Act 1988 or under the terms of a licence issued by the Copyright Licensing Agency Ltd, 90 Tottenham Court Road, London, England W1T 4LP. Applications for the copyright holder's written permission to reproduce any part of this publication should be addressed to the publisher

British Library Cataloguing in Publication Data

A catalogue record for this book is available from the British Library

Library of Congress Cataloguing in Publication Data A catalogue record for this book is available from the Library of Congress

ISBN 0 7506 4331 5

DOCKE

Printed and bound by Antony Rowe Ltd, Eastbourne

For more information on all Newnes publications please visit our website at www.newnespress.com





- line time base In TV the circuits responsible for generating the signals causing horizontal deflection of the *scanning beam*. In modern TV receivers the line output stage generates, in addition to the line scanning current, a direct voltage to boost the supply to the output stage, the heater supply for the picture tube, the EHT supply for the picture tube and possibly a low-voltage supply for early stages in the receiver.
- **liquid crystal display (LCD)** A display system consisting essentially of a very thin layer of liquid sandwiched between two conducting glass plates between which the control voltage is applied. One way in which the applied voltage controls the light transmission of the device is by varying the light scattering in the liquid which is specially chosen because of its long-molecule construction. The conducting areas of the plates are such that, by applying voltages to certain of the leads, specified areas of the display can be illuminated by light transmitted through the device or reflected at the rear glass plate. Thus a seven-segment pattern can be used to give a numerical display.

Liquid crystal displays consume very little electrical power compared with *light-emitting diode* displays and have superseded LEDS in batteryoperated calculators and digital watches.

Lissajous figures Patterns generated on the screen of a *cathode ray tube* when the *electron beam* is defected horizontally and vertically by sinusoidal signals with a simple relationship between their frequencies. Some typical patterns are shown in *Figure L.9*.



Figure L.9 Some typical Lissajous figures

Litz wire See skin effect.

L-network A network consisting of one series and one shunt element. See Figure L.10.

load (1) Of any signal source the circuit connected across its terminals and into which it delivers power. See *anode load*. (2) In computers and data