Fundamentals of Automatic Control

Robert C. Weyrick Community and Technical College The University of Akron

McGraw-Hill Book Company

New York	Montreal
St. Louis	New Delhi
Dallas	Panama
San Francisco	Paris
Düsseldorf	São Paulo
Johannesburg	Singapore
Kuala Lumpur	Sydney
London	Tokyo
Mexico	Toronto

TSMC et al v. Zond IPR2014-00799 Page 1 Zond Ex. 2011 ess Cataloging in Publication Data

of automatic control.

ontrol. I. Title. 74-10896

-1

ALS OF AUTOMATIC CONTROL

975 by McGraw-Hill, Inc. All rights reserved. United States of America. No part of this publication uced, stored in a retrieval system, or transmitted, in 7 any means, electronic, mechanical, photocopying, recording, vithout the prior written permission of the publisher.

) KPKP 78321098765

his book were Alan W. Lowe and g, the designer was Tracy A. Glasner, on was supervised by Valerie Klima and Laurence Charnow. dallion by York Graphic Services, Inc. nd bound by Kingsport Press, Inc.

134771

TJ 213 VV43

To my mother

TSMC et al v. Zond IPR2014-00799 Page 2 Zond Ex. 2011 itals of automatic control



Figure 1-8 Takeoff-point representation

es being combined at a summing point must be in the same ample, two voltages may be combined but a voltage and nuot be brought together. Any number of variables may ning point.

point is used when the output of a block is applied to two ks. A takeoff point is simply represented by a dot as shown

ite the block-diagram representation of a system, let us ne the oven-temperature control described in the preceding system is shown in block-diagram form in Fig. 1-9. In this agram the various blocks may be identified with elements 1. In addition the units associated with the transfer function is are shown in parentheses.

diagram tends to clarify the physical understanding of the provides a convenient basis for system analysis. We shall t block diagrams are useful in pointing out the similarity parently unrelated systems. It should be emphasized that nnecting one block with another represent the flow of rmation within the system. The main sources of energy for need not be included in the block diagram.

1-6 SIMPLIFICATION OF BLOCK DIAGRAMS

: diagram that is initially drawn for a system may contain ther of blocks and signal paths and be more complicated rable. In such cases a simplification may be performed to block diagram to a form with fewer blocks. Rearranging





Figure 1-10 Moving summing point around a block

a system diagram to effect simplification is termed *block-diagram algebra* since it is analogous to simplifying algebraic equations. However, reducing a block diagram has the advantage of providing a better understanding of the interrelationships of the various elements in the system as compared to simplifying the system equations.

The combining of cascaded blocks into a single block, as described in Sec. 1-5, is obviously one step toward simplification. As another possibility, it is sometimes useful to move a summing point around a block as indicated in Fig. 1-10. Note that the inputs A and B are introduced through blocks incorporating the function G around which the summing point was moved. Applying the distributive property of algebra, we see that C = (A + B)G = AG + BG. Thus the two diagrams are equivalent.

Table 1-1 gives a number of transformations useful in simplifying block diagrams. These transformations can be verified by showing that the outputs from the two equivalent diagrams are the same. Note that the original and equivalent identities can be used interchangeably.

1-7 CLOSED-LOOP TRANSFER FUNCTION

Since certain functions and types of variables are commonly associated with feedback control systems, a generalized block diagram may be formulated and the associated closed-loop transfer function derived. Some standardization of the symbols and terminology relating to feedback control systems has been achieved and is used in this case.

Figure 1-11 is a general block diagram of a closed-loop control system. It is important that the terms used in this diagram be clearly understood.

System Variables

The desired value V is an external signal applied to the system to command a specific output from the process. The desired value is TSMC et al v. Zond IPR2@14907Pmes called the system command or set point.

Figure 1-9 Block diagram of oven-temperature control Page 3 Zond Ex. 2011



G_v Reference input elements G, Control elements

- G₂ System elements or process
- H Feedback elements
- / Desired value
- Reference input
- Controlled output
- Manipulated variable
- Disturbance input
- Feedback signal
- Error or actuating signal

Figure 1-11 General block diagram of control system

C

M

E

Ε

The reference input R is derived from the desired value and is a signal external to the control loop. It serves as the reference of comparison for the feedback signal.

The controlled output C is the process quantity being controlled.

The manipulated variable M is the control signal which the control elements apply to the process.

The feedback signal B is a signal which is a function of the controlled output and which is summed with the reference input.

The error or actuating signal E is the algebraic difference between the reference input and feedback signals and provides the signal applied to the control elements.

The disturbance input U is an unwanted input signal to the system that tends to cause the controlled output to differ from the value commanded by the reference input. Disturbance inputs are due to changes in the load on the system. For example, a change in the ambient temperature surrounding the oven described in Sec. 1-3 is a disturbance since it changes the heat input required by the oven. Obviously the response of the system to a disturbance input should be minimal.

System Elements

The reference input elements G_v convert the desired value to a reference input signal.

The control elements G_1 , sometimes called the controller, are the components that act on the error signal and generate a control signal to the process.

The feedback elements H are the components required to measure or sense the value of the controlled output and convert it to a usable feedback signal.

feedback signal. TSMC et al v. Zond IPR2014-00799 Page 4 Zond Ex. 2011