

CAP-101/PROV

3-21-01

AIPROV

Please type a plus sign (+) inside this box

Approved for use through 10/31/2002. OMB 0651-0032
U.S. Patent and Trademark Office, U.S. DEPARTMENT OF COMMERCE

Under the Paperwork Reduction Act of 1995, no persons are required to respond to a collection of information unless it displays a valid OMB control number.

PROVISIONAL APPLICATION FOR PATENT COVER SHEET

This is a request for filing a PROVISIONAL APPLICATION FOR PATENT under 37 CFR 1.53(c).

Express Mail Label No. ET 0506 2712 4 US

JC490 U.S. PTO

U.S. PTO
60/277217
03/19/01

INVENTOR(S)					
Given Name (first and middle [if any])		Family Name or Surname		Residence (City and either State or Foreign Country)	
Jeffrey P.		Wilde		Los Gatos, CA	
<input type="checkbox"/> Additional inventors are being named on the ___ separately numbered sheets attached hereto					
TITLE OF THE INVENTION (280 characters max)					
Reconfigurable Optical Add-Drop Multiplexer with Dynamic Spectral Equalization Capability for DWDM Optical Networking Applications					
Direct all correspondence to: CORRESPONDENCE ADDRESS					
<input type="checkbox"/> Customer Number		<input type="text"/>		<input type="text"/>	
OR		Type Customer Number here		Place Customer Number Bar Code Label here	
<input checked="" type="checkbox"/> Firm or Individual Name		Capella Photonics, Inc.			
Address		c/o Jeffrey P. Wilde			
Address		19 Great Oaks Blvd., Suite 10			
City		San Jose		State CA ZIP 95119	
Country		USA		Telephone (408) 360-4240 Fax (408) 225-6248	
ENCLOSED APPLICATION PARTS (check all that apply)					
<input checked="" type="checkbox"/> Specification		Number of Pages <input type="text" value="18"/>		<input type="checkbox"/> CD(s), Number <input type="text"/>	
<input checked="" type="checkbox"/> Drawing(s)		Number of Sheets <input type="text" value="22"/>		<input type="checkbox"/> Other (specify) <input type="text"/>	
<input type="checkbox"/> Application Data Sheet. See 37 CFR 1.76					
METHOD OF PAYMENT OF FILING FEES FOR THIS PROVISIONAL APPLICATION FOR PATENT					
<input checked="" type="checkbox"/> Applicant claims small entity status. See 37 CFR 1.27.				FILING FEE AMOUNT (\$)	
<input checked="" type="checkbox"/> A check or money order is enclosed to cover the filing fees				75.00	
<input type="checkbox"/> The Commissioner is hereby authorized to charge filing fees or credit any overpayment to Deposit Account Number:		<input type="text"/>			
<input type="checkbox"/> Payment by credit card. Form PTO-2038 is attached.					
The invention was made by an agency of the United States Government or under a contract with an agency of the United States Government.					
<input checked="" type="checkbox"/> No.					
<input type="checkbox"/> Yes, the name of the U.S. Government agency and the Government contract number are: _____					

Respectfully submitted,
SIGNATURE Jeffrey P. Wilde
TYPED or PRINTED NAME Jeffrey P. Wilde
TELEPHONE (408) 360-4243

Date 3/17/01
REGISTRATION NO.
(if appropriate)
Docket Number:

USE ONLY FOR FILING A PROVISIONAL APPLICATION FOR PATENT

This collection of information is required by 37 CFR 1.51. The information is used by the public to file (and by the PTO to process) a provisional application. Confidentiality is governed by 35 U.S.C. 122 and 37 CFR 1.14. This collection is estimated to take 8 hours to complete, including gathering, preparing, and submitting the complete provisional application to the PTO. Time will vary depending upon the individual case. Any comments on the amount of time you require to complete this form and/or suggestions for reducing this burden, should be sent to the Chief Information Officer, U.S. Patent and Trademark Office, U.S. Department of Commerce, Washington, D.C. 20231. DO NOT SEND FEES OR COMPLETED FORMS TO THIS ADDRESS. SEND TO: Box Provisional Application, Assistant Commissioner for Patents, Washington, D.C. 20231.

PROVISIONAL PATENT APPLICATION OF

JEFFREY P. WILDE

for

**RECONFIGURABLE OPTICAL ADD-DROP MULTIPLEXER WITH
DYNAMIC SPECTRAL EQUALIZER CAPABILITY FOR
DWDM OPTICAL NETWORKING APPLICATIONS**

FIELD OF THE INVENTION

This invention relates generally to optical communication hardware, and more specifically to hardware designed for use in dense wavelength division multiplexed (DWDM) systems. The invention describes a new device design for providing two important functions of importance in emerging DWDM systems: (1) reconfigurable add-drop of individual wavelength channels, and (2) spectral equalization of wavelength channels.

SUMMARY & DETAILED DESCRIPTION

The more detailed disclosure of the present invention is contained in the following description and figures, as supplied by the attached appendices.

Appendix A: Design Concept for DWDM Multi-Channel Dynamic Add/Drop Module,
by J. P. Wilde, 7/28/00

Appendix B: Modified Dynamic OADM Design, by J. P. Wilde, 11/28/00

Appendix C: Reconfigurable OADM with Dynamic Equalization, by J. P. Wilde,
12/28/00

Appendix D: Technical Specifications 1/9/2001, Dynamic Optical Add/Drop Multiplexer

Overview and Objective

Emerging DWDM communication systems are in need of a robust and low-cost device technology for providing dynamic optical add-drop of wavelength channels at node sites as shown in Figures 1 and 2. Such a device -- referred to as an optical add-drop multiplexer (OADM) -- should be remotely reconfigurable through software control. It is desirable to have complete control at the granularity of a single wavelength, meaning any individual wavelength channel can be added/dropped by the device.

Long-haul and ultra-long-haul applications require the OADM to support a large channel count (80 channels today, heading to 160 channels or more in the future). Therefore, a technology that is intrinsically scalable to such channel counts is needed. Moreover, it is important that the optical loss introduced by the device be independent (or only weakly dependent) on the number of channels. The device should also have low polarization

dependent loss (PDL) and low polarization mode dispersion (PMD). A general set of device specifications is outlined in Appendix D.

Figures 3 and 4 illustrate two basic approaches, parallel and serial, to constructing a dynamic OADM. The parallel architecture is intrinsically scalable to large channel counts, and is the general approach taken in this invention. The serial scheme has various limitations as noted in Figure 4.

A parallel architecture based on free-space optics has been previously described in Ref. 1. A block diagram of this device is shown in Figure 5. It has four fiber ports: (1) input, (2) pass-through, (3) add, and (4) drop. One circulator is used to combine the input and pass-through ports onto one fiber, and another circulator combines the add and drop ports to a second fiber. Figure 6 shows a graphic of the optical system configuration of the OADM device described in Ref. 1. Two coupling lenses are implemented to convert the light paths from these two fibers to free space. Wavelength separation and routing are done in free space. The device utilizes a ruled diffraction grating to separate the input light into its constituent channels. A binary micromachined mirror array redirects each of the individual channels to one of two outputs. Each mirror in the linear array either retroreflects its corresponding channel back along the original input path towards the pass-through port, or it reflects its channel to the drop port.

While this architecture is attractive in the sense that it is compact and scalable to high channel count, it also has a number of limitations. First, the design requires precise alignment of components that makes assembly during fabrication complex and expensive. Second, no provisions are provided for maintaining the relative alignment of the optical components so that the system performance may degrade over time, or in the presence of shock and vibrations, or due to a temperature change. Third, it requires all the add and drop wavelengths to enter and leave the device on single fibers. In other words, additional means must be provided to multiplex the add channels onto a single fiber and to demultiplex the drop channels from the single fiber output from the device. This additional mux/demux requirement can lead to significant additional expense.

What is needed is an improved free-space architecture that overcomes these limitations.

Description of the Invention

The OADM device architecture disclosed here has all the positive attributes of a compact, parallel design, and also overcomes existing limitations by providing (1) a more versatile architecture with multiple physical add and drop ports, (2) analog mirrors under servo control that loosen fabrication tolerances and provide self-alignment to correct for component drift during operation, (3) additional optics to provide the servo feedback signal, and (4) a servo system scheme that provides for dynamic spectral equalization on a channel-by-channel basis.

OADM Architectures

Three different OADM architectures disclosed in the present invention are shown in Figures 7-9. All of these architectures provide for dynamic drop of one or more wavelength channels on any one of multiple drop ports. The “wavelength separation and routing” (WSR) function is common to all three architectures and is performed using free-space optics and silicon micromirrors. The optical loss of the WSR unit can be fairly low, its value being determined by the diffraction efficiency of a grating or similar dispersive device used for wavelength separation. A typical value is in the range from 2 - 4 dB. For the preferred case in which only one wavelength is dropped on each drop port, then no additional wavelength demultiplexing is required before the signals carried by the respective channels are received by photodetectors. The three approaches of Figs. 7-9 differ primarily in the way in which the add function is implemented.

The first of these (Fig. 7) is designed for one-way optical propagation. It uses a combiner (or 1xN coupler; e.g., the 1x16 broadband coupler sold by Newport Corp., Irvine, CA, product model number F-CPL-B16350) for injecting the add channels into the pass-through port. While use of a combiner is straightforward, the associated optical loss can be large (e.g., the 1x16 Newport coupler may have up to 14.5 dB of loss). For those situations where the loss can be tolerated, this is suitable approach.

The second architecture (Fig. 8) is designed for bi-directional operation and has better loss performance compared to the first embodiment. Two WSR units are utilized, with one unit providing dynamic drop and the other dynamic add. This architecture is very general, with no fundamental restrictions on the wavelengths that can be added or dropped (other than those restrictions imposed by the overall communication system).

The third architecture (Fig. 9) is also bi-directional, but uses only one WSR unit. Circulators are situated on all of the physical input/output ports, allowing for two-way optical propagation. This design has the restriction that at each of the add/drop ports, the add and drop wavelengths must be the same.

Free-Space Optical Embodiments

One embodiment of the present invention is shown in Figure 10. The input/output consists of a linear array of fiber collimators. Such collimators are well known in the art and are comprised of a collimating lens and ferrule-mounted fiber packaged together in a mechanically rigid stainless steel or glass tube (e.g., see collimators made by ADC Photonics, Inc., Minneapolis, MN, www.adc.com). The collimators can be positioned in a linear array by, for example, means of a V-groove array made out of any of a variety of materials including silicon, plastic, or ceramic. The top collimator is designated the input, the second collimator is designated the pass-through, and the remaining collimators are designated as drop ports.

Multi-wavelength light from the input collimator is directed to a ruled diffraction grating. The grating separates the different wavelength channels into different diffraction angles.

In the preferred embodiment, -1 order diffraction is assumed. A focusing lens receives the diffracted light and focuses it onto a linear micromirror array positioned in the back focal plane. The lens has the property that it brings the different wavelength channels to focus at separate spatial locations such that each channel is associated with a unique focused spot. Each wavelength channel is associated with a single mirror in the micromirror array. Figure 10 illustrates only three wavelengths for simplicity. Figure 11 shows a close-up view of the micromirror array, with each of the three wavelengths falling on its respective mirror.

Each of the mirrors in the micromirror array reflects its associated wavelength channel back through the focusing lens, to the grating, and back towards one of output ports. This requires the micromirrors to be dynamically adjustable with at least one axis of rotation. The rotational motion should be under analog control, so that the angles can be continuously adjusted to scan across all possible output collimator ports. Various types of micromachined mirrors and deflectors exist in the art. One prior art implementation is shown here in Figure 12. This is an array of reflective ribbons, the position of each ribbon being under electrostatic control (made by Silicon Light Machines, Inc., Sunnyvale, CA). An adaptation of such a ribbon array can be used in the present invention to provide the micromirror function, with each ribbon in the array acting as a separately controllable mirror.

In the preferred embodiment, the grating is placed in the front focal plane of the focusing lens, thereby producing a telecentric optical system. A telecentric system has the property that the chief rays of the focused beams are all parallel to each other and generally parallel to the optical axis. In this application, the telecentric design allows the reflected beams to efficiently couple back into the output collimators, with little translational walk-off error (perpendicular to the vertical collimator array plane). A quarter wave plate is placed in front of the focusing lens to provide the desired polarization properties as discussed in Ref. 1 (namely minimal PDL and PMD).

By controlling independently the angle of each micromirror, the system has the ability to direct each wavelength channel to any of the outputs (pass-through or drop). The presence of multiple drop ports allows for the possibility of putting only one wavelength on one drop port, thereby avoiding the additional demultiplexing (and the associated cost and complexity) that would otherwise be required with the prior art device of Figures 5 and 6. Feedback control of the mirror positions makes the system stable. More detail regarding the control system is provided in the following sections. This system can readily scale to large channel count by simply adding more mirrors to the mirror array.

The results of an optical ray trace model are shown in Figures 13-15. The collimated beam diameter is approximately 1 mm. The angle of incidence on the grating is 85 degrees, and the grating spatial frequency is 700 lines/mm. The grating is blazed to optimize the -1 order diffraction efficiency. An $f=30$ mm ideal focusing lens captures the diffracted light and focuses it to the micromirror plane (denoted as the spatial light modulator (SLM) plane in Figures 13-15). In this model, the grating is not placed in the front focal plane of the focusing lens, so this configuration does not represent the

Explore Litigation Insights

Docket Alarm provides insights to develop a more informed litigation strategy and the peace of mind of knowing you're on top of things.

Real-Time Litigation Alerts



Keep your litigation team up-to-date with **real-time alerts** and advanced team management tools built for the enterprise, all while greatly reducing PACER spend.

Our comprehensive service means we can handle Federal, State, and Administrative courts across the country.

Advanced Docket Research



With over 230 million records, Docket Alarm's cloud-native docket research platform finds what other services can't. Coverage includes Federal, State, plus PTAB, TTAB, ITC and NLRB decisions, all in one place.

Identify arguments that have been successful in the past with full text, pinpoint searching. Link to case law cited within any court document via Fastcase.

Analytics At Your Fingertips



Learn what happened the last time a particular judge, opposing counsel or company faced cases similar to yours.

Advanced out-of-the-box PTAB and TTAB analytics are always at your fingertips.

API

Docket Alarm offers a powerful API (application programming interface) to developers that want to integrate case filings into their apps.

LAW FIRMS

Build custom dashboards for your attorneys and clients with live data direct from the court.

Automate many repetitive legal tasks like conflict checks, document management, and marketing.

FINANCIAL INSTITUTIONS

Litigation and bankruptcy checks for companies and debtors.

E-DISCOVERY AND LEGAL VENDORS

Sync your system to PACER to automate legal marketing.