

When all these features come together in one compact, lightweight, and power-efficient unit, you have the ultimate in flexible networking--the Linksys Instant Wireless Access Point.

of network security. The Instant Wireless Access Point is easy to install (Just plug it in and you're ready to go!) and easy to use--Windows-based diagnostics and

The Instant Wireless Access Point's high-powered antenna offers a range of operation of up to 800 feet, providing seamless roaming throughout your wireless LAN infrastructure; an advanced user authentication feature ensures a high level

WPC11

WUSB1



statistic tools ensure that you'll always be in control.

9/5/2016 Product Specifications

Wayback Machine

http://www.linksys.com/products/product.asp?prid=157&grid=19

l<mark>at</mark>ic a la admille a latete e d

Go

43 captures 14 Apr 01 - 2 Jul 16

Detailed Picture of this Product

User Guide for this Product (in PDF)

Product Datasheet (in PDF)

Features

- High-Speed Transfer Rate of Up to 11 Mbps
- Interoperable with IEEE 802.11b (DSSS) 2.4GHz-compliant Equipment
- Provides Roaming, Best Access Point Selection, Load Balancing, and Network Traffic Filtering
- Supports up to 32 users/nodes
- Long Operating Range Supports 120m (indoor) and 300m (outdoor)
- Hardware Wired Equivalent Privacy
- Works with all standard Internet Applications
- Technical Support 24 Hours a Day, 7 Days a Week in North America Only.
- Full 1-Year Warranty

Specs

- 1. Standards IEEE 802.3 (wired), IEEE 802.11b (wireless)
- 2. Channels
 - i. 11 Channels (US, Canada)
 - ii. 13 Channels (Europe)
 - iii. 14 Channels (Japan)
- 3. Ports One 10BaseT/RJ-45 Port
- 4. Cabling Type 10BaseT: UTP/STP Category 3 or 5
- 5. Operating Range
 - i. Indoor:
 - 50M (164 ft.) @ 11 Mbps
 - 80M (262 ft.) @ 5.5 Mbps
 - 120M (393 ft.) @ 2 Mbps,
 - 150M (492 ft.) @ 1 Mpbs
 - ii. Outdoor:
 - 250M (820 ft.) @ 11 Mbps
 - 350M (1148 ft.) @ 5.5 Mbps
 - 400M (1312 ft.) @ 2 Mbps



9/5/2016 Product Specifications



http://www.linksys.com/products/product.asp?prid=157&grid=19

<mark>lal</mark>a a la minulli a lalair e d

Go

43 captures 14 Apr 01 - 2 Jul 16

















©Copyright 2001 Linksys Group Inc. All rights reserved.

