



INTERNATIONAL TELECOMMUNICATION UNION

ITU-T

TELECOMMUNICATION
STANDARDIZATION SECTOR
OF ITU

G.711

**GENERAL ASPECTS OF DIGITAL TRANSMISSION
SYSTEMS**

TERMINAL EQUIPMENTS

**PULSE CODE MODULATION (PCM) OF
VOICE FREQUENCIES**

ITU-T Recommendation G.711

(Extract from the *Blue Book*)

NOTES

1 ITU-T Recommendation G.711 was published in Fascicle III.4 of the *Blue Book*. This file is an extract from the *Blue Book*. While the presentation and layout of the text might be slightly different from the *Blue Book* version, the contents of the file are identical to the *Blue Book* version and copyright conditions remain unchanged (see below).

2 In this Recommendation, the expression “Administration” is used for conciseness to indicate both a telecommunication administration and a recognized operating agency.

© ITU 1988, 1993

All rights reserved. No part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from the ITU.

PULSE CODE MODULATION (PCM) OF VOICE FREQUENCIES

(Geneva, 1972; further amended)

1 General

The characteristics given below are recommended for encoding voice-frequency signals.

2 Sampling rate

The nominal value recommended for the sampling rate is 8000 samples per second. The tolerance on that rate should be ± 50 parts per million (ppm).

3 Encoding law

3.1 Eight binary digits per sample should be used for international circuits.

3.2 Two encoding laws are recommended and these are commonly referred to as the A-law and the μ -law. The definition of these laws is given in Tables 1a/G.711 and 1b/G.711 and Tables 2a/G.711 and 2b/G.711 respectively.

When using the μ -law in networks where suppression of the all 0 character signal is required, the character signal corresponding to negative input values between decision values numbers 127 and 128 should be 00000010 and the value at the decoder output is -7519. The corresponding decoder output value number is 125.

3.3 The number of quantized values results from the encoding law.

3.4 Digital paths between countries which have adopted different encoding laws should carry signals encoded in accordance with the A-law. Where both countries have adopted the same law, that law should be used on digital paths between them. Any necessary conversion will be done by the countries using the μ -law.

3.5 The rules for conversion are given in Tables 3/G.711 and 4/G.711.

3.6 *Conversion to and from uniform PCM*

Every "decision value" and "quantized value" of the A (resp. μ) law should be associated with a "uniform PCM value". (For a definition of "decision value" and "quantized value", see Recommendation G.701 and in particular Figure 2/G.701). This requires the application of a 13 (14) bit uniform PCM code. The mapping from A-law PCM, and μ -law PCM, respectively, to the uniform code is given in Tables 1/G.711 and 2/G.711. The conversion to A-law or μ -law values from uniform PCM values corresponding to the decision values, is left to the individual equipment specification. One option is described in Recommendation G.721, § 4.2.8 subblock COMPRESS.

4 Transmission of character signals

When character signals are transmitted serially, i.e. consecutively on one physical medium, bit No. 1 (polarity bit) is transmitted first and No. 8 (the least significant bit) last.

The relationship between the encoding laws of Tables 1/G.711 and 2/G.711 and the audio signal level is defined as follows:

A sine-wave signal of 1 kHz at a nominal level of 0 dBm0 should be present at any voice frequency output of the PCM multiplex when the periodic sequence of character signals of Table 5/G.711 for the A-law and of Table 6/G.711 for the μ -law is applied to the decoder input.

The resulting theoretical load capacity (T_{\max}) is +3.14 dBm0 for the A-law, and +3.17 dBm0 for the μ -law.

Note - The use of another digital periodic sequence representing a nominal reference frequency of 1020 Hz at a nominal level of -10 dBm0 (preferred value, see Recommendation O.6) or 0 dBm0 is acceptable, provided that the theoretical accuracy of that sequence does not differ by more than ± 0.03 dB from a level of -10 dBm0 or 0 dBm0 respectively. In accordance with Recommendation O.6, the specified frequency tolerance should be 1020 Hz + 2 Hz, -7 Hz.

If a sequence representing -10 dBm0 is used, the nominal value at the voice frequency outputs should be -10 dBm0.

TABLE 1a/G.711
A-law, positive input values

1	2	3	4	5	6	7	8
Segment number	Number of intervals × interval size	Value at segment end points	Decision value number n	Decision value x_n (see Note 1)	Character signal before inversion of the even bits	Quantized value (value at decoder output) y_n	Decoder output value number
					Bit number 1 2 3 4 5 6 7 8		
7	16 × 128	4096	(128)	(4096) -	-----	4032	128
			127	3968	1 1 1 1 1 1 1 1		
6	16 × 64	2048	113	2176	(see Note 2)	2112	113
			112	2048	1 1 1 1 0 0 0 0		
5	16 × 32	1024	97	1088	(see Note 2)	1056	97
			96	1024	1 1 1 0 0 0 0 0		
4	16 × 16	512	81	544	(see Note 2)	528	81
			80	512	1 1 0 1 0 0 0 0		
3	16 × 8	256	65	272	(see Note 2)	264	65
			64	256	1 1 0 0 0 0 0 0		
2	16 × 4	128	49	136	(see Note 2)	132	49
			48	128	1 0 1 1 0 0 0 0		
1	32 × 2	64	33	68	(see Note 2)	66	33
			32	64	1 0 1 0 0 0 0 0		
↓			1	2	(see Note 2)		
			0	0	1 0 0 0 0 0 0 0	1	1

Note 1 - 4096 normalized value units correspond to $T_{max} = 3.14 \text{ dBm0}$.

Note 2 - The character signals are obtained by inverting the even bits of the signals of column 6. Before this inversion, the character signal corresponding to positive input values between two successive decision values numbered n and $n + 1$ (see column 4) is $(128 + n)$ expressed as a binary number

Note 3 - The value at the decoder output is $y_n = \frac{x_{n-1} + x_n}{2}$ for $n = 1, \dots, 127, 128$.

Note 4 - x_{128} is a virtual decision value.

Note 5 - In Tables 1/G.711 and 2/G.711 the values of the uniform code are given in columns 3, 5 and 7.

Explore Litigation Insights

Docket Alarm provides insights to develop a more informed litigation strategy and the peace of mind of knowing you're on top of things.

Real-Time Litigation Alerts



Keep your litigation team up-to-date with **real-time alerts** and advanced team management tools built for the enterprise, all while greatly reducing PACER spend.

Our comprehensive service means we can handle Federal, State, and Administrative courts across the country.

Advanced Docket Research



With over 230 million records, Docket Alarm's cloud-native docket research platform finds what other services can't. Coverage includes Federal, State, plus PTAB, TTAB, ITC and NLRB decisions, all in one place.

Identify arguments that have been successful in the past with full text, pinpoint searching. Link to case law cited within any court document via Fastcase.

Analytics At Your Fingertips



Learn what happened the last time a particular judge, opposing counsel or company faced cases similar to yours.

Advanced out-of-the-box PTAB and TTAB analytics are always at your fingertips.

API

Docket Alarm offers a powerful API (application programming interface) to developers that want to integrate case filings into their apps.

LAW FIRMS

Build custom dashboards for your attorneys and clients with live data direct from the court.

Automate many repetitive legal tasks like conflict checks, document management, and marketing.

FINANCIAL INSTITUTIONS

Litigation and bankruptcy checks for companies and debtors.

E-DISCOVERY AND LEGAL VENDORS

Sync your system to PACER to automate legal marketing.