

EXHIBIT 6



IN THE U.S. PATENT AND TRADEMARK OFFICE

Appl. No. : 12/387,661
 Applicant : Jari LINDHOLM et al.
 Filing date : May 5, 2009

TC/AU : 2819 (confirmation no. 2958)
 Examiner : Crystal L. HAMMOND

Atty Docket : 863.0099.U1(US)
 Customer No. : 29,683

Title : METHOD, APPARATUS AND COMPUTER PROGRAM FOR POWER CONTROL RELATED TO RANDOM ACCESS PROCEDURES

Commissioner for Patents
 P.O. Box 1450
 Alexandria, VA 22313-1450

AMENDMENT

Sir:

In response to the non-final Office Action dated October 3, 2011, the Applicant hereby amends the above-referenced application as follows:

Amendments to the Written Description: None.

Amendments to the Drawings: None.

Amendments to the Claims: begins at page 2 of this paper.

Remarks/Arguments: begins at page 9 of this paper.

Appendix: None.

This Amendment is filed within two months following the shortened statutory period for reply recited in the referenced Office Action. The Applicants hereby petition for a two month time extension and the undersigned representative authorizes the US Patent Office to deduct the one-month late fee (\$560) from Deposit Account No. 50-1924. Should the undersigned representative be mistaken as to time or fee, please consider this as a petition for an extension of time necessary to effect his Amendment and/or charge Deposit Account No. 50-1924 for any required fee deficiency.

03/05/2012 CCHAU1 00000047 501924 12387661
 01 FC:1252 560.00 DA

US Patent Application Ser No. 12/387,661
Art Unit 2819: confirmation no. 2598

AMENDMENTS TO THE CLAIMS:

This listing of claims will replace all prior versions, and listings, of claims in this application.

1.(Original) A method comprising:

using a processor to initialize for $i=0$ a first power control adjustment state $g(i)$ for an uplink control channel and a second power control adjustment state $f(i)$ for an uplink shared channel to each reflect an open loop power control error;

using the processor to compute an initial transmit power for the uplink shared channel using full pathloss compensation, wherein the initial transmit power depends on a preamble power of a first message sent on an access channel, and is initialized with the second power control adjustment state $f(0)$; and

sending from a transmitter a third message on the uplink shared channel at the initial transmit power.

2.(Original) The method according to claim 1, wherein the first message comprises a random access request message, the method further comprising:

computing the preamble power using full pathloss compensation,

sending from the transmitter on the access channel the first message and in response receiving at a receiver a second message that comprises an allocation of resources on which the third message is sent;

and after sending the third message, the method further comprises using the processor to compute an updated transmit power for the uplink shared channel using fractional power control and sending from the transmitter a subsequent message on the uplink shared channel using the updated transmit power.

3.(Original) The method according to claim 1, wherein the second power control adjustment state $f(i)$ for $i=0$ is initialized as:

$$P_{0_UE_PUSCH} + f(0) = \Delta P_{PC} + \Delta P_{rampup};$$

US Patent Application Ser No. 12/387,661
Art Unit 2819; confirmation no. 2598

wherein: $P_{0_UE_PUSCH}$ is a power control constant for the uplink shared channel that is specific for a user equipment executing the method;

ΔP_{rampup} is a ramp-up power for preamble transmissions; and

ΔP_{PC} is a power control command indicated in a second message that is received in response to sending the first message.

4.(Previously Presented) The method according to claim 1, wherein the first power control adjustment state $g(i)$ for $i=0$ is initialized as:

$$P_{0_UE_PUCCH} + g(0) = \Delta P_{PC} + \Delta P_{rampup};$$

wherein: $P_{0_UE_PUCCH}$ is a power control constant for the uplink control channel power that is specific for a user equipment executing the method.

5.(Original) The method according to claim 4, wherein $P_{0_UE_PUSCH} = P_{0_UE_PUCCH} = 0$ when computing initial values at $i=0$ of power control states for the respective shared and control channels.

6.(Previously Presented) The method according to claim 1,

wherein the initial transmit power P_{Msg3} of the third message for $i=0$ is equal to:

$$P_{Msg3} = \min\{P_{max}, P_{preamble} + \Delta_{0,preamble_Msg3} + \Delta_{PC_Msg3} + 10 \log_{10}(M_{PUSCH}(i)) + \Delta_{TF}(TF(i))\};$$

in which: P_{MAX} is a maximum allowed transmission power;

$P_{preamble}$ is the preamble power of the first message;

$M_{PUSCH}(i)$ is determined from an uplink resource allocation of a second message received in response to sending the first message;

$\Delta_{TF}(TF(i))$ is calculated from received signaling;

Δ_{PC_Msg3} is indicated by a power control command received at the receiver; and

US Patent Application Ser No. 12/387,661
 Art Unit 2819; confirmation no. 2598

$\Delta_{0,preamble_Msg3}$ is an offset from the preamble power.

7.(Original) A method according to claim 6, further comprising, after sending the third message, using the processor to compute an updated transmit power for the shared uplink channel using fractional power control and sending from the transmitter a subsequent message on the uplink shared channel using the updated transmit power, wherein the updated transmit power $P_{PUSCH}(i)$ is equal to:

$$P_{PUSCH}(i) = \min\{P_{MAX}, 10 \log_{10}(M_{PUSCH}(i)) + P_{O_PUSCH}(j) + \alpha \cdot PL + \Delta_{TF}(TF(i)) + f(i)\};$$

wherein: $P_{O_PUSCH}(j)$ is calculated from received signaling,

α or an indication of α is received in signaling, and

PL is path loss that is estimated from received signaling.

8.(Original) The method according to claim 7, wherein $\alpha=1$ for the third message and for all retransmissions of the third message indicating full pathloss compensation, and $\alpha<1$ for messages after the third message and all retransmissions of the third message indicating fractional pathloss compensation.

9.(Original) The method according to claim 8, executed by a user equipment; and wherein the third message comprises an indication of a power difference between the initial transmit power which is computed using full pathloss compensation and a fractional pathloss computation of the initial transmit power.

10.(Original) A computer readable memory storing a computer program that when executed by a processor results in actions comprising:

initializing for $i=0$ a first power control adjustment state $g(i)$ for an uplink control channel and a second accumulation power control adjustment state $f(i)$ for an uplink shared channel to each reflect an open loop power control error;

computing an initial transmit power for the uplink shared channel using full pathloss compensation, wherein the initial transmit power depends on a preamble power of a first

Explore Litigation Insights

Docket Alarm provides insights to develop a more informed litigation strategy and the peace of mind of knowing you're on top of things.

Real-Time Litigation Alerts



Keep your litigation team up-to-date with **real-time alerts** and advanced team management tools built for the enterprise, all while greatly reducing PACER spend.

Our comprehensive service means we can handle Federal, State, and Administrative courts across the country.

Advanced Docket Research



With over 230 million records, Docket Alarm's cloud-native docket research platform finds what other services can't. Coverage includes Federal, State, plus PTAB, TTAB, ITC and NLRB decisions, all in one place.

Identify arguments that have been successful in the past with full text, pinpoint searching. Link to case law cited within any court document via Fastcase.

Analytics At Your Fingertips



Learn what happened the last time a particular judge, opposing counsel or company faced cases similar to yours.

Advanced out-of-the-box PTAB and TTAB analytics are always at your fingertips.

API

Docket Alarm offers a powerful API (application programming interface) to developers that want to integrate case filings into their apps.

LAW FIRMS

Build custom dashboards for your attorneys and clients with live data direct from the court.

Automate many repetitive legal tasks like conflict checks, document management, and marketing.

FINANCIAL INSTITUTIONS

Litigation and bankruptcy checks for companies and debtors.

E-DISCOVERY AND LEGAL VENDORS

Sync your system to PACER to automate legal marketing.