



US00623000B1

(12) **United States Patent**
Taylor

(10) **Patent No.:** **US 6,230,000 B1**
(45) **Date of Patent:** **May 8, 2001**

(54) **PRODUCT DETECTOR AND METHOD THEREFOR**

(75) Inventor: **Daniel Richard Taylor**, Phoenix, AZ (US)

(73) Assignee: **Motorola Inc.**, Schaumburg, IL (US)

(*) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 0 days.

(21) Appl. No.: **09/173,030**

(22) Filed: **Oct. 15, 1998**

(51) Int. Cl.⁷ **H04B 1/26; H04B 1/00**

(52) U.S. Cl. **455/323; 455/303; 455/304; 455/313**

(58) Field of Search **455/302, 303, 455/304, 324, 338, 339, 313, 318, 323; 375/323, 329, 332; 327/113, 45; 329/304**

(56) **References Cited**

U.S. PATENT DOCUMENTS

4,847,860	*	7/1989	Robert	375/136
4,878,029		10/1989	Saulnier et al.	329/341
5,150,124		9/1992	Moore et al.	342/68
5,339,459		8/1994	Schiltz et al.	455/333
5,355,103	*	10/1994	Kozak	455/289
5,557,642		9/1996	Williams	375/316
5,761,615	*	6/1998	Jaffee	455/314
5,805,093		9/1998	Heikkila et al.	
5,838,675	*	11/1998	Rauscher	370/343
5,999,574	*	12/1999	Sun et al.	375/326
6,073,001	*	6/2000	Sokoler	455/323
6,088,581	*	7/2000	Bickley et al.	455/131

FOREIGN PATENT DOCUMENTS

0691733 6/1995 (EP) **H03B/21/00**

2294169	9/1995	(GB)	H03D/7/00
9110283	12/1990	(WO)	H03D/3/00
9602977	7/1995	(WO)	H04B/1/26
9838732	2/1998	(WO)	H03D/7/00

OTHER PUBLICATIONS

Article entitled "A 1.5 GHz Highly Linear CMOS Down-conversion Mixer" published in IEEE Journal of Solid-State Circuits, vol. 30, No. 7, Jul. 1995.

Article entitled "Recent Advances in Shortwave Receiver Design" by Dr. Ulrich L. Rohde in QST, Nov. 1992.

Article "Asymmetric Polyphase Networks" by M.J. Gingell in Electrical Communication, vol. 48, No. 1 and 2, 1973.

Article entitled "High-Performance, Single-Signal Direct-Conversion Receivers" by Rick Campbell—QST Magazine (Jan. 1993).

* cited by examiner

Primary Examiner—Dwayne Bost


Assistant Examiner—Raymond B. Persino

(74) Attorney, Agent, or Firm—Dana B. LeMoine; Timothy J. Lorenz; Frank J. Bogacz

(57) **ABSTRACT**

A product detector for converting a signal to baseband includes a commutating switch which serves to sample an RF waveform four times per period at the RF frequency. The samples are integrated over time to produce an average voltage at 0 degrees, 90 degrees, 180 degrees and 270 degrees. The average voltage at 0 degrees is the baseband in-phase signal, and the average voltage at 90 degrees is the baseband quadrature signal. Alternatively, to increase gain, the 0 degree average can be differentially summed with the 180 degree average to form the baseband in-phase signal, and the 90 degree average can be differentially summed with the 270 degree average to produce the baseband quadrature signal.

14 Claims, 3 Drawing Sheets



INTEL 1004




FIG. 1
- PRIOR ART -




FIG. 2
- PRIOR ART -




FIG. 4





FIG. 5



30 FIG. 3




FIG. 6 170




FIG. 7

PRODUCT DETECTOR AND METHOD THEREFOR

FIELD OF THE INVENTION

This invention relates in general to radio receivers and, in particular, to the converting of signals in frequency.

BACKGROUND OF THE INVENTION

Direct conversion receivers are desirable in part because they convert signals of interest directly to baseband (or near zero hertz) from a radio frequency (RF) or an intermediate frequency (IF). Simple direct conversion receivers, such as receiver 10 shown in FIG. 1, suffer from multiple drawbacks. The RF signal f_1 is mixed with the local oscillator signal f_0 , and the signal of interest $f_1 - f_0$ is produced at baseband at the output. Unfortunately, superimposed on the signal of interest is the image $f_0 - f_1$. The "image problem" of simple direct conversion receivers is well known in the art of receiver design, the solution to which has been the subject of scholarly study for decades.

Image reject mixers, such as mixer 20 in FIG. 2, have been developed in response to the image problem suffered by simple direct conversion receivers. The operation of image reject mixers, including the mathematical basis upon which they operate, is described in detail in "High-Performance, Single-Signal Direct-Conversion Receivers" by Rick Campbell, published in the January, 1993 issue of QST magazine. Image reject mixers utilize two local oscillator signals, each differing from the other by 90 degrees in phase. Image reject mixers also require the use of two separate mixer elements. Image reject receivers represent a complex and expensive solution to the image problem of direct conversion receivers.

Both simple direct conversion receivers and image reject mixers nominally exhibit a loss of 6 dB because half of the signal is converted to $f_0 + f_1$, the sum of the RF frequency and the local oscillator frequency, and then discarded. In practice, the loss is often greater than 6 dB because conventional mixers are typically implemented with diodes which exhibits a finite amount of loss themselves. Typical conversion loss in prior art image reject mixers is 7-8 dB.

What is needed is a low-loss method and apparatus for simply and inexpensively overcoming the image problem of direct conversion receivers.

BRIEF DESCRIPTION OF THE DRAWING

- FIG. 1 shows a prior art direct conversion receiver;
- FIG. 2 shows a prior art image reject mixer;
- FIG. 3 shows a direct conversion receiver in accordance with a preferred embodiment of the present invention;
- FIG. 4 shows a waveform in accordance with a preferred embodiment of the present invention;
- FIG. 5 shows a product detector in accordance with a preferred embodiment of the present invention;
- FIG. 6 shows a product detector in accordance with an alternate embodiment of the present invention; and
- FIG. 7 shows a product detector in accordance with an alternate embodiment of the present invention.

DETAILED DESCRIPTION OF THE DRAWINGS

The method and apparatus of the present invention represent a simple and inexpensive product detector which facilitates the conversion of a signal to baseband without the unwanted image from interfering. A commutating switch is

used in combination with capacitors to integrate portions of the input signal. The in-phase and quadrature signals that result represent the signal of interest at baseband.

Turning now to the drawings in which like reference characters indicate corresponding elements throughout the several views, attention is first directed to FIG. 3. FIG. 3 shows a direct conversion receiver in accordance with a preferred embodiment of the present invention. Direct conversion receiver 30 includes resistor 32, bias network 34, commutating switch 38, capacitors 72, 74, 76, and 78, summing amplifiers 50 and 52, phase delay 58, and summing amplifier 60.

In operation, an RF or IF signal f_1 is received at resistor 32. Resistor 32, as is more fully discussed below, forms a filter when taken in combination with capacitors 72-78. After passing through resistor 32, the input signal is received by commutating switch 38 at input 36. Commutating switch 38 switches input 36 to outputs 42, 44, 46, and 48. The rate at which commutating switch 38 operates is controlled by a signal present at control input 40. In the preferred embodiment as shown in FIG. 3, the control signal input to control input 40 is substantially equal to four times the local oscillator frequency that would exist in a simple direct conversion receiver. As a result, input 36 is switched to each of the four outputs substantially once during each period of the input signal f_1 .

In a preferred embodiment, commutating switch 38 remains closed at each of the four outputs for substantially 90 degrees at the frequency of the input signal. In alternate embodiments, commutating switch 38 remains closed at each of the four outputs for less than 90 degrees.

During the time that commutating switch 38 connects input 36 to output 42, charge builds up on capacitor 72. Likewise, during the time commutating switch 38 connects input 36 to output 44, charge builds up on capacitor 74. The same principle holds true for capacitors 76 and 78 when commutating switch 38 connects input 36 to outputs 46 and 48 respectively. As commutating switch 38 cycles through the four outputs, capacitors 72-78 charge to voltage values substantially equal to the average value of the input signal during their respective quadrants. Each of the capacitors functions as a separate integrator, each integrating a separate quarter wave of the input signal. This principle is described more fully with respect to FIG. 4 below.

Output 42 represents the average value of the input signal during the first quarter wave of the period, and is termed the 0 degree output. Output 44 represents the average value of the input signal during the second quarter wave of the period, and is termed the 90 degree output. Output 46 represents the average value of the input signal during the third quarter wave of the period, and is termed the 180 degree output. Output 48 represents the average value of the input signal during the fourth quarter wave of the period, and is termed the 270 degree output.

The outputs of commutating switch 38 are input to summing amplifiers 50 and 52. Summing amplifier 50 differentially sums the 0 degree output and the 180 degree output, thereby producing baseband in-phase signal 54. Summing amplifier 52 differentially sums the 90 degree output and the 270 degree output, thereby producing baseband quadrature signal 56. Baseband in-phase signal 54 and baseband quadrature signal 56 are input to phase delay 58 which shifts the phase of baseband quadrature signal 56 by 90 degrees relative to baseband in-phase signal 54. The resulting signals are then summed by summing amplifier 60 to produce the signal of interest 62.

Explore Litigation Insights

Docket Alarm provides insights to develop a more informed litigation strategy and the peace of mind of knowing you're on top of things.

Real-Time Litigation Alerts



Keep your litigation team up-to-date with **real-time alerts** and advanced team management tools built for the enterprise, all while greatly reducing PACER spend.

Our comprehensive service means we can handle Federal, State, and Administrative courts across the country.

Advanced Docket Research



With over 230 million records, Docket Alarm's cloud-native docket research platform finds what other services can't. Coverage includes Federal, State, plus PTAB, TTAB, ITC and NLRB decisions, all in one place.

Identify arguments that have been successful in the past with full text, pinpoint searching. Link to case law cited within any court document via Fastcase.

Analytics At Your Fingertips



Learn what happened the last time a particular judge, opposing counsel or company faced cases similar to yours.

Advanced out-of-the-box PTAB and TTAB analytics are always at your fingertips.

API

Docket Alarm offers a powerful API (application programming interface) to developers that want to integrate case filings into their apps.

LAW FIRMS

Build custom dashboards for your attorneys and clients with live data direct from the court.

Automate many repetitive legal tasks like conflict checks, document management, and marketing.

FINANCIAL INSTITUTIONS

Litigation and bankruptcy checks for companies and debtors.

E-DISCOVERY AND LEGAL VENDORS

Sync your system to PACER to automate legal marketing.